

# 15502 Repeater

## OVERVIEW

The NotifEye™ Repeater extends the normal operating range of a wireless network. It is used to bridge the gap between NotifEye sensors and the NotifEye gateway when the distance between them is too long for a direct connection. Data coming from the sensor is delivered to the repeater and forwarded to the gateway at a rate of 6 messages per minute.

FEATURES	BENEFITS
<ul style="list-style-type: none"> <li>• Extends coverage area (range) of your network (250-300 ft)</li> <li>• AC powered</li> <li>• Supports up to 100 sensors</li> <li>• Stores up to 30,000 messages if gateway is unavailable</li> <li>• LED status/activity light</li> </ul>	<ul style="list-style-type: none"> <li>• Allows for greater distance between sensors and gateways</li> <li>• No batteries required</li> <li>• Reduces congestion from multi-sensor networks</li> <li>• Data is stored in the event of gateway power loss</li> <li>• Four visual alerts to identify network connectivity               <ul style="list-style-type: none"> <li>- Flashing red &amp; green: Looking for a gateway to connect to</li> <li>- Solid red: No gateway found</li> <li>- Solid green: Has connected to a gateway</li> <li>- Flashing green: Sensor data is intercepted and relayed</li> </ul> </li> </ul>
<p><b>Specifications:</b></p> <ul style="list-style-type: none"> <li>• Dimensions: (L x W x H) 3.09" x 2.085" x 1.417" (78 mm x 53 mm x 36 mm)</li> <li>• Antenna: 7.25" (184 mm) with SMA connector</li> <li>• Communication: 900 MHz</li> <li>• Power: AC</li> <li>• 1-year warranty</li> </ul>	

